

PC-900 Printer Installation Instruction

PC-900



First step: take out the battery

-



Bottom of the monitor

Second step: take out the screws



The screws are to fix the
front panel
Screw: ST3×12

Third step: open the front panel

-




Fourth step: Separate front and rear parts of the monitor

-




Fifth step: take out screws from the main frame



The screws are to fix the main frame

Sixth step: take out the main frame (with module)


-



Replace the
printer cover
with the printer

Power cable
(connected
to the printer)


Printer module



Signal cable port

Power cable port

Main board



**Main Signal cable port
(connected to
interface board)**

**Signal cable port
(connected to
printer)**

Finished

- Kindly note: pls turn off the monitor and take out the battery before dismantle the monitor.